



HIGHCROSS®

# HighCross IR codes

## IR codes for ECM-IR4B device (revision 1.04)

The ECM-IR4B module allows to receive commands from external devices via multiple IR channels. To do it installer has to setup ports to IR receive mode and/or turn on internal IR receiver.

The module supports up to 255 unique IR commands and sends received commands to external controllers as channel push/release events.

### Table of supported IR codes

All IR codes have the repeating part. As a result the "push" message will be active as long as the button is pressed.

CHANNEL NUMBER	IR CODE (PHILIPS PRONTO FORMAT)
1	0000 006a 0000 0008 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
2	0000 006a 0000 0008 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
3	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
4	0000 006a 0000 0008 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
5	0000 006a 0000 0008 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
6	0000 006a 0000 0008 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
7	0000 006a 0000 0008 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
8	0000 006a 0000 0008 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
9	0000 006a 0000 0008 004f 004f 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
10	0000 006a 0000 0008 0019 0082 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
11	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
12	0000 006a 0000 0008 0019 0082 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
13	0000 006a 0000 0008 004f 004f 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
14	0000 006a 0000 0008 0019 0082 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
15	0000 006a 0000 0008 004f 004f 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 0019 055b
16	0000 006a 0000 0008 0019 0082 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
17	0000 006a 0000 0008 004f 004f 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
18	0000 006a 0000 0008 0019 0082 004f 004f 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
19	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
20	0000 006a 0000 0008 0019 0082 0019 0082 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
21	0000 006a 0000 0008 004f 004f 0019 0082 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
22	0000 006a 0000 0008 0019 0082 004f 004f 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
23	0000 006a 0000 0008 004f 004f 004f 004f 004f 004f 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
24	0000 006a 0000 0008 0019 0082 0019 0082 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
25	0000 006a 0000 0008 004f 004f 0019 0082 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
26	0000 006a 0000 0008 0019 0082 004f 004f 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
27	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
28	0000 006a 0000 0008 0019 0082 0019 0082 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
29	0000 006a 0000 0008 004f 004f 0019 0082 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
30	0000 006a 0000 0008 0019 0082 004f 004f 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
31	0000 006a 0000 0008 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 0019 055b
32	0000 006a 0000 0008 0019 0082 0019 0082 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 055b
33	0000 006a 0000 0008 004f 004f 0019 0082 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 055b
34	0000 006a 0000 0008 0019 0082 004f 004f 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 055b
35	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 0019 0082 0019 0082 004f 004f 0019 0082 0019 0082 0019 055b











*Continue*

CHANNEL NUMBER	IR CODE (PHILIPS PRONTO FORMAT)
251	0000 006a 0000 0008 004f 004f 004f 004f 0019 0082 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0523
252	0000 006a 0000 0008 0019 0082 0019 0082 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0523
253	0000 006a 0000 0008 004f 004f 0019 0082 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0523
254	0000 006a 0000 0008 0019 0082 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0523
255	0000 006a 0000 0008 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 004f 0523